


[VIE]

 HyperWork

HƯỚNG DẪN SỬ DỤNG

Wireless Mouse




Hộp bao gồm:

- 1* Chuột
- 1* Hướng dẫn sử dụng
- 1* USB-A Receiver
- 1* USB Type-C Receiver
- 1* Cáp sạc USB-A to Type-C

Công tắc nguồn

Cổng sạc Type-C



USB-A Receiver


Type-C Receiver

Nút chuyển tiếp




Nút quay lại

Nút chuyển đổi chế độ /
Nút kết nối Bluetooth



Đèn báo màu trắng tắt
khi kết nối thành công



Đèn đỏ sẽ nhấp nháy khi pin yếu.
Đèn đỏ sáng khi đang sạc.
Đèn xanh khi sạc đầy

-  Nhấn nút chuyển đổi chế độ để chuyển sang chế độ 2.4G USB-A, đèn trắng ở vị trí số 1 sáng lên rồi tắt.
-  Nhấn nút chuyển đổi chế độ để chuyển sang chế độ 2.4G Type-C, đèn trắng ở vị trí số 2 sáng lên rồi tắt.
-  Nhấn lại nút chuyển đổi chế độ để chuyển sang chế độ Bluetooth, đèn trắng ở vị trí số 3 sáng lên rồi tắt.

Kết nối Receiver 2.4G

1. Bật công tắc nguồn.
2. Lấy Receiver USB-A hoặc Type-C ra khỏi chỗ để nằm ở phía sau nắp đáy của chuột.
3. Cắm Receiver vào cổng tương ứng của máy tính.
4. Nhấn vào nút chuyển đổi chế độ để chuyển sang kênh USB-A 2.4G, đèn trắng của  sẽ sáng một lúc và sau đó chuột được kết nối thành công.
4. Nhấn vào nút chuyển đổi chế độ để chuyển sang kênh Type-C 2.4G, đèn trắng của  sẽ sáng một lúc và sau đó chuột được kết nối thành công.

Kết nối Bluetooth

1. Bật công tắc nguồn.
2. Nhấn nút chuyển đổi chế độ của chuột sang chế độ Bluetooth, đèn báo nhấp nháy một lần, sau đó nhấn và giữ trong 3 giây, chuột chuyển sang chế độ ghép nối Bluetooth và đèn báo nhấp nháy nhanh.
3. Mở bảng kết nối Bluetooth trên thiết bị, nhấn vào tìm kiếm thiết bị Bluetooth rồi tìm “HPW-MS1” trong danh sách và Kết nối (Không cần mật khẩu để kết nối).

Chú ý:

1. Nếu chuột không kết nối và sử dụng được. Vui lòng lặp lại các bước trên để kết nối lại và sử dụng.
2. Nếu muốn các thiết bị khác kết nối với chuột, vui lòng làm theo các bước trên để kết nối lại chuột.
3. Nếu các thiết bị khác được kết nối lại với kênh Bluetooth hiện có, chuột sẽ mặc định lưu vào bộ nhớ của thiết bị được kết nối lần cuối.

Thông số kỹ thuật

DPI	800 - 1200 - 1600 - 2400
Dung lượng Pin	300 mAh
Thời gian chờ	600 giờ
Khoảng cách truyền hiệu quả	Bán kính 10 mét
Dòng điện hoạt động	≤ 2 mA
Thời gian làm việc liên tục	300 giờ
Kích thước sản phẩm	107.5*69.5*41.5mm
Thời gian nghỉ (Sleep Mode)	Sau 30 phút không hoạt động
Thoát khỏi Sleep Mode	Nhấn nút bất kỳ để sử dụng lại

Thông báo sạc

1. Đèn báo màu đỏ nhấp nháy khi mức pin của chuột quá thấp. Vui lòng sạc sản phẩm kịp thời.
2. Đường truyền của chuột sẽ bị trễ, đơ và kết nối không ổn định.

Phương pháp kết nối lại chế độ Receiver

Trong trường hợp không thể kết nối, hãy làm theo các bước sau để cài đặt lại toàn bộ thiết lập mặc định của chuột:


1. Bật công tắc nguồn của chuột, nhấn nút chuyển chế độ để chọn kênh USB-A hoặc Type-C.
2. Nhấn và giữ nút chuột trái, con lăn và nút chuột phải trong 5 giây cho đến khi đèn báo nhấp nháy nhanh, sau đó bỏ tay ra.
3. Cắm đầu thu USB-A hoặc Type-C vào cổng USB-A hoặc Type-C của máy tính.
4. Kết nối thành công khi đèn hiển thị kết nối USB-A hoặc Type-C màu trắng sáng rồi tắt.

[ENG]



USER MANUAL

Wireless Mouse




Packing List

- 1* Mouse
- 1* User manual
- 1* USB Receiver
- 1* Type-C Receiver
- 1* USB To Type-C charging cable

Power switch

Type-C charging interface



USB receiver inside


Type-C receiver inside

Page Forward Button

Page Back Button

Mode Switch Button /
Bluetooth Pairing Button

Channel indicator, the
white indicator light turns off
when the connection is successful.



Red light will flash when battery power
is too low.

The red light is always on when
charging, green light when full
charged.



Press the mode switch button to switch to 2.4G-USB channel, and the white light of No. 1 lights up and goes out.



Press the mode switch button to switch to 2.4G-Type-C channel, and the white light of No. 1 lights up and goes out.



Press the mode switch button again, it is the buletooeeh channel, and the white light of No. 3 lights up and goes out.

2.4G Connection

1. Turn on the mouse power switch.
2. Take out the USB receiver from the receiver hole on the bottom of the mouse.
3. Plug the USB receiver into your computer's USB port.
4. Click the mouse mode switch button to switch to the 2.4G USB channel, the white light of channel 1 will be on for a while, and then the mouse is successfully connected.
5. Click the mouse mode switch button to switch to the 2.4G Type-C channel, the white light of channel 2 will be on for a while, and then the mouse is successfully connected.

Bluetooth Connection

1. Turn on the mouse power switch.
2. Press the mode switch button of the mouse to channel 3, the indicator light flashes once, then press and hold for 3 seconds, the mouse enters the Bluetooth pairing mode, and the indicator light flashes quickly.
3. Turn on the bluetooth function on your computer settings,click the bluetooth search and then find "HPW-MS01" in the search list and click connect(No bluetooth pairing password required)

Note:

1. If the mouse not connected and used normally, please repeat the above steps to reconnect and use.
- 2.If you want the Bluetooth of other devices to continue to connect the mouse, please follow the above steps to reconnect the mouse Bluetooth.
3. If other devices are reconnected to the existing Bluetooth channel, the mouse default to the memory of the last connected device.

Mouse Specifications

DPI	800-1200 (default) -1600 - 2400
Battery specifications	300 mAh
Standby time	600 hours
Effective transmission distance	Within 10 meters
Working current	≤ 2 mA
Continuous working time	300 hours
Product Size	107.5*69.5*41.5mm
Sleep time	Sleeps for 30 minutes after no operation
Wake-up method	Press any key to wake up

Product charging

1. The red indicator light will start to flash when the power of the mouse is too low. Please charge the product in time.
2. The transmission of the mouse will be delayed, stuck, and the connection will be unstable.

2.4G mode re-pairing method

We completed the 2.4G mode pairing during the product production process. If you plug the USB receiver into the computer and turn on the power switch, the keyboard or mouse is no response, can not use normally, please re-pairing by yourself. The mouse can be paired separately as follows steps.

1. Turn on the power switch of the mouse, Click once to select USB or Type-C channel,
2. Press and hold the left mouse button, the scroll wheel, and the right mouse button together for 5 seconds until the indicator light flashes quickly.
3. Plug the USB or Type-C receiver into your computer USB or Type-C port.
4. The connection is successful when the white indicator light is on and then off.